

Poly Studio Base Room Kit for Zoom Rooms

Product Brief

Poly Base Room Kit¹ transforms outdated meeting spaces into modern Zoom Rooms, enhancing productivity and communication.



Seamless Room Transformation

Transform your BYOD room with the Poly Base Room Kit¹, featuring an HP collaboration PC with a robust Intel® Core™ i7 CPU². Effortlessly control your meetings using the sleek 10-inch Poly TC10 touch controller.

Skit the Configuration

Certified and built for Zoom Rooms and qualified for Intelligent Director³, this powerful meeting room solution offers a consistent user experience and are straightforward for IT to setup.

Enterprise-grade Management

Poly Lens remote device management gives you better visibility into workspaces across the entire organization. With multiple ways to manage, IT professionals can remotely monitor, update, and troubleshoot Poly devices on their own terms.

Recommended Ecosystem



Poly Studio V-Series (V32/V52/V72)
USB video bars



Poly Studio V-Series (V32/V52/V72)
USB video bars



Poly Studio E70
(including 3 x E70 Intelligent
Director camera kit)



Poly Studio E60



Poly Studio Base Room Kit for Zoom Rooms Product Brief

HP Mini Conferencing PC with Zoom Rooms

Form factor	Mini
Operating System	Windows 11 IoT Enterprise 64 ¹
Processor family	12th generation Intel ^(R) Core ^(TM) i7 processor
Processor	Intel ^(R) Core ^(TM) i7-12700T (up to 4.7 GHz with Intel ^(R) Turbo Boost Technology, 25MB L3 cache, 12 cores, 20 threads) ^{3,4,5}
Chipset	Intel ^(R) Q670 (vPro ^(R)) ⁶
Memory	16 GB DDR5-4800 MHz RAM (2 x 8 GB) ^{7,8}
Internal Storage	256 GB PCIe ^(R) NVMe ^(TM) TLC SSD ⁹
Graphics	Integrated
Graphics (integrated)	Intel ^(R) UHD Graphics 770
Minimum dimensions (W x D x H)	6.97 x 6.89 x 1.35 in (17.7 x 17.5 x 3.4 cm)
Weight	3.13 lb (1.42kg) (Exact weight depends on configuration)
I/O Ports (Front)	1 headset connector; 1 SuperSpeed USB Type-A 10Gbps signaling rate; 1 SuperSpeed USB Type-A 10Gbps signaling rate (charging), 1 Super-speed USB Type-C ^(R) 20 Gbps signaling rate
I/O Ports (Rear)	1 RJ-45; 3 SuperSpeed USB Type-A 10Gbps signaling rate; 2 DisplayPort ^(TM) 1.4; 1 HDMI 2.0b; 1 power connector
Expansion Slot	1 M.2 2230; 2 M.2 2280 (1 M.2 2230 slot for WLAN and 2 M.2 2280 slots for storage)
Package dimensions (W x D x H)	49.8 x 13.2 x 23.5 cm (Packaging material used will vary by Country)
Package weight	2.95 kg
Wireless	Intel ^(R) Wi-Fi 6E AX211 (2x2) and Bluetooth ^(R) 5.3 wireless card (supporting gigabit data rate) ¹⁰
Power	90 W external power adapter, up to 89% efficiency
Management features	HP Image Assistant, HP Manageability Integration Kit ¹² Poly Lens/ Poly Lens Room
Security management	HP Sure Start Gen7
What's included	HP Mini Conferencing PC with Zoom Rooms; AC adapter; power cord; 1 HP DisplayPort to HDMI True 4K adapter; HP Desktop Mini Security/ Dual VESA Sleeve v3 with Power Supply Holder



Poly Studio Base Room Kit for Zoom Rooms Product Brief

Poly TC10 IP Touch Controller

Display size	10.1 inch (diagonal)
Panel technology	IPS
Minimum dimensions (W x D x H)	10.25 x 7.25 x 2.5 in (260 x 184 x 64 mm)
Resolution	WXGA (1280 x 800)
Aspect ratio	16:10
Viewing angle	75° (up/down/left/right)
Positioning angle	60° or 30° (on tabletop surface)
Ports	1 RJ-45
Weight	2.79 lb (1.27 kg)
Package dimensions (W x D x H)	190 x 210 x 55 mm
Package weight	300 g
What's included?	Poly TC10; Wall mount kit; Table stand; Mounting hardware; RJ-45 cable; Quick Start QR code; Warranty card; Poly Lens coaster



Poly Studio V72 Product Brief

MESSAGING FOOTNOTES

1. Poly base kit for Zoom Rooms includes a Poly TC10 touch control panel and HP Mini Conferencing PC with 12th Gen Intel® Core™ i7. Zoom Rooms license is required and sold separately. Complete Zoom Rooms requires audio and video device, not included in the Poly Studio Base Room Kit.
2. Multi-Core is designed to improve performance of certain software products. Not all customers or software applications will necessarily benefit from use of this technology. Performance and clock frequency will vary depending on application workload and your hardware and software configurations. Intel's numbering, branding and/or naming is not a measurement of higher performance.
3. Zoom Intelligent Director requires minimum of two Poly Studio E70 or Poly Studio E60 cameras. Poly Studio E70 camera kit, sold separately, includes three Poly Studio E70 cameras with power supplies. Required and sold separately for the complete Poly Studio Solution for Zoom Rooms solution are the following: Poly Base Room Kit for Zoom Rooms, which includes a Poly TC10 touch control panel and HP Mini Conferencing PC with Zoom Rooms; Poly Trio C60 conference phone is available for audio or room Digital Signal Processor (DSP) can be connected to the Collaboration PC; and a Zoom Rooms license.
4. Recycled plastic is expressed as a percentage of the total weight plastic. Post-consumer recycled is based on the definition set in the EPEAT standard for computers, IEEE 1680.1-2018 standard.
5. Percent of paper-based packaging made from sustainably sourced, certified, and recycled fibers.

TECHNICAL SPECIFICATIONS FOOTNOTE

1. Not all features are available in all editions or versions of Windows. Systems may require upgraded and/or separately purchased hardware, drivers, software or BIOS update to take full advantage of Windows functionality. Windows is automatically updated and enabled. High speed internet and Microsoft account required. ISP fees may apply and additional requirements may apply over time for updates. See <http://www.windows.com>
3. For full Intel® vPro® functionality, Windows 11 Pro 64 bit, a vPro supported processor, vPro enabled chipset, vPro enabled wired LAN and/or WLAN card and TPM 2.0 are required. Some functionality requires additional 3rd party software in order to run. See <http://intel.com/vpro>
4. Multi-core is designed to improve performance of certain software products. Not all customers or software applications will necessarily benefit from use of this technology. Performance and clock frequency will vary depending on application workload and your hardware and software configurations. Intel's numbering, branding and/or naming is not a measurement of higher performance.
5. Intel® Turbo Boost technology requires a PC with a processor with Intel Turbo Boost capability. Intel Turbo Boost performance varies depending on hardware, software and overall system configuration. See <http://www.intel.com/technology/turboboost> for more information.
6. For full Intel® vPro® functionality, Windows 11 Pro 64 bit, a vPro supported processor, vPro enabled chipset, vPro enabled wired LAN and/or WLAN card and TPM 2.0 are required. Some functionality requires additional 3rd party software in order to run. See <http://intel.com/vpro>.
7. For systems configured with more than 3 GB of memory and a 32-bit operating system, all memory may not be available due to system resource requirements. Addressing memory above 4 GB requires a 64-bit operating system. Memory modules support data transfer rates up to 4800 MT/s; actual data rate is determined by the system's configured processor. See processor specifications for supported memory data rate. All memory slots are customer accessible/upgradeable.
8. All memory slots are customer accessible/upgradeable.
9. For storage drives, GB = 1 billion bytes. TB = 1 trillion bytes. Actual formatted capacity is less. Up to 30 GB (for Windows) of disk is reserved for system recovery software.
10. Wi-Fi 6E requires a Wi-Fi 6E router, sold separately, to function in the 6GHz band. Availability of public wireless access points limited. Wi-Fi 6E is backwards compatible with prior 802.11 specs. And available in countries where Wi-Fi 6E is supported.
11. Based on US EPEAT® registration according to IEEE 1680.1-2018 EPEAT®. Status varies by country. Visit www.epeat.net for more information.
12. HP Manageability Integration Kit can be downloaded from <http://www.hp.com/go/clientmanagement>.

© Copyright 2024 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

